



Non-Reversing, Three Pole Starters With AC Coil, Series CAT4 (Open type only) ❶

I_e [A]		Ratings for Switching AC Motors (AC2 / AC3 / AC4)										Auxiliary Contacts per Contactor		Open Type Catalog Number	Price
		kW (50 Hz)				UL/CSA HP (60 Hz)									
		230V	415V 400V	500V	690V	1 Ø		3 Ø							
AC-3	AC-1		115V			230V	200V	230V	460V	575V	NO	NC			
9	20	12	9	7	~	.75	1.5	3	3	5	5	1	0	CAT4-9-10-✕-◆	94
												0	1	CAT4-9-01-✕-◆	94



CAT4-9-10... starter



CAT4-9C-10... starter


Non-Reversing, Three Pole Starters With DC Coil, Series CAT4 (Open type only) ❶❷

I_e [A]		Ratings for Switching AC Motors (AC2 / AC3 / AC4)										Auxiliary Contacts per Contactor		Open Type Catalog Number	Price
		kW (50 Hz)				UL/CSA HP (60 Hz)									
		230V	415V 400V	500V	690V	1 Ø		3 Ø							
AC-3	AC-1		115V			230V	200V	230V	460V	575V	NO	NC			
9	20	12	9	7	~	.75	1.5	3	3	5	5	1	0	CAT4-9C-10-✱-◆	114
												0	1	CAT4-9C-01-✱-◆	114

Reversing, Three Pole Starters With AC Coil, Series CAUT4 (Open type only) ❶❸❹

I_e [A]		Ratings for Switching AC Motors (AC2 / AC3 / AC4)										Auxiliary Contacts per Contactor		Open Type Catalog Number	Price
		kW (50 Hz)				UL/CSA HP (60 Hz)									
		230V	415V 400V	500V	690V	1 Ø		3 Ø							
AC-3	AC-1		115V			230V	200V	230V	460V	575V	NO	NC ③			
9	20	12	9	7	~	.75	1.5	3	3	5	5	0	1	CAUT4-9-02-✱-◆-LW	167
												2	1	CAUT4-9-42-✱-◆-PW	207

Note: Reversing CA4 starters with DC coils will not accept a mechanical interlock and are not available.



CAUT4-9-42...PW reversing starter

CAUT4...LW Includes:

- Mechanical interlock
- Select either solid state or electromechanical Overload Relay Code from Section C

CAUT4...PW Includes:

- Mechanical and electrical interlock ❸
- Reversing power and control wiring (using Wiring Kit Cat.# KCR4)
- Top mount auxiliary contact block (Cat.# CS4-P20)
- Select *only* solid state Overload Relay Code from Section C ❹

A.C. Coil Codes ❶

A.C. Coil Code	Voltage Range	
	50 Hz	60 Hz
24	24V	24V
120	110V	110V-120V
240	220V-230V	230V-240V
277	240V	277V
380	400V-415V	380V-400V

D.C. Coil Codes ❶

D.C. Coil Codes	Voltage
24D	24V
48D	48V
110D	110V
220D	220V

Ordering Instructions

- Specify Catalog Number
- Replace (★) With Coil Code
- Replace (◆) With O/L Relay Code ❹

Coil Codes on this page
O/L Relay Code on A93

- ❶ CA4 not available without coil. Coils and contacts not replaceable.
- ❷ Select Coil Code from D.C. Coil Code table only.
- ❸ NC contacts on each contactor are used for electrical interlocking.
- ❹ If selecting CAUT4-9-42-★-◆-PW reversing starter, only use Overload Relay Code for a CEP7 solid state overload relay. CT4 Thermal Overload Relay is not compatible with power wiring kit.