


Indicator Actuator and Fuseblock with Signaling Switches



Dimensional Data



CATALOG SYMBOL: KAZ
INDICATOR
VOLTAGE RATING: 600 VOLTS
INTERRUPTING RATING: 200,000 A
U.L. LISTED (GUIDE # JDVS, FILE # E58836)

13/32" x 2" (10.3mm x 50.8mm) FUSEBLOCKS WITH
MINIATURE SIGNALING SWITCHES
600 VOLT RATING
U.L. RECOGNIZED
(GUIDE # QEUY2, FILE # E61918)

Type KAZ Actuator (not a fuse).

13/32" x 2" (10.3mm x 50.8mm)


- Connects in parallel with fuses having a rating of 50 amperes or larger.
- Opens at 10A or more.
- When used with Buss signal blocks, actuates a miniature switch which closes a signal circuit when fuse opens. Device also gives a direct visual indication of an open fuse by ejected (spring actuated) end pin.
- Mounts in Buss signal blocks 2778, 2837 and 2838.
- U.L. Listed as "fuse accessory".

CE logo denotes compliance with European Union Low Voltage Directive (50-1000 VAC, 75-1500 VDC). Refer to BIF document #8002 or contact Bussmann Application Engineering at 314-527-1270 for more information.

Cat. No.	Poles	Dimensions ± 1/31" (0.8mm)			Mounting Data		
		Inches/(mm's)	A	B	C	Hole	C'Bore
2778	1	1.75 (44.5)	—	2.5 (63.5)	1.73	0.328	#8
2837*	2	5.31 (134.9)	4.81 (122.2)	3 (76.2)	0.250	—	#12
2838*	3	6.63 (168.3)	6.125 (155.6)	3 (76.2)			

* Includes fuseclips to hold spare KAZ.

Dimensional Data



The only controlled copy of this BIF document is the electronic read-only version located on the Bussmann Network Drive. All other copies of this BIF document are by definition uncontrolled. This bulletin is intended to clearly present comprehensive product data and provide technical information that will help the end user with design applications. Bussmann reserves the right, without notice, to change design or construction of any products and to discontinue or limit distribution of any products. Bussmann also reserves the right to change or update, without notice, any technical information contained in this bulletin. Once a product has been selected, it should be tested by the user in all possible applications.