

Plug Fuses



Fustat Fuse Adaptors

Fustat Adaptors (various ampere ratings) screw into the "Edison" Thread fuse sockets of standard household fuse boxes. Adaptors serve the purpose of preventing the wrong size fuse from being used.

Catalog Number	Symbol and Amperes	Carton	
		Qty.	Wt.
SA- (Branch Circuits)	15, 20, 30	4	0.03 (lbs)
SA- (Single Motor Circuits)	1, 1¼, 1½, 2, 2½, 3½, 4, 5, 6¼, 8, 10		
EDA	Edison base dummy		
ENA	Edison base neutral		

Dual-Element Fustat® Fuses and Adaptors for Small Motor Protection.

(Both Motor Running and Short-Circuit Protection)

Fuses Cat No.	Adapter Cat. No.	Other Accepted Ampere Ratings
S¾, S½, S⅔, S⅑, S⅒, S⅓, S⅔, S1	SA1	1 amp and Smaller
S1⅙, S1¼	SA1¼	All smaller
S1¼, S1⅔	SA1⅔	All smaller
S1⅑, S2	SA2	—
S2¼, S2½	SA2½	1⅑, 2
S2⅔, S3, S3⅔	SA3⅔	1⅑, 2, 2¼, 2½
S3½, S4	SA4	—
S4½, S5	SA5	3½, 4
S5⅑, S6¼	SA6¼	3½, 4, 4½, 5
S7, S8	SA8	—
S9, S10	SA10	7, 8
S12, S14	SA15	7, 8, 9, 10
Branch Circuit Protection		
S15	SA15	—
S20	SA20	—
S25	SA30	—
S30	SA30	20, 25, 30

