


PART NUMBER SELECTION TABLES

Screw Clamp 15 mm DIN-Rail Terminals Feed Through


WDU 1.5/R 3.5

new



WDK 1.5/R 3.5

new



Available Options	Version	Type	Part No.	Type	Part No.
	Wemid	WDU 1.5/R 3.5	1753280000	WDK 1.5/R 3.5	1753290000
	Blue Wemid	WDU 1.5/R 3.5 BL	1754170000	WDK 1.5/R 3.5 BL	1754180000
Dimensions					
Width / Length / Height mm (in.) with TS 15 x 7.5		3.5/24.5/25 (.14/.96/.98)		3.5/46.5/38.5 (.14/1.83/1.52)	
Insulation stripping length / screw size / screw slot size		7 (-1) mm / M 2/0.4 x 2.5		7 (-1) mm / M 2/0.4 x 2.5	
Technical Data					
Rated voltage / rated current / wire size		UL 300 V / 15 A / #26...14 AWG		300 V / 15 A / #26...14 AWG	
	CSA	300 V / 10 A / #26...14 AWG		300 V / 10 A / #26...14 AWG	
	VDE	400 V / 17.5 A / 1.5 mm ²		400 V / 17.5 A / 1.5 mm ²	
Rated impulse voltage/pollution severity		1.5 kV/3		1.5 kV/3	
Tightening torque range		Nm 0.27		0.27	
End Plate / Partition					
WAP (thickness 1.5 mm)		Wemid	WAP WDU 1.5/R 3.5	1754190000	WAP WDK 1.5/R 3.5
Jumpers					
ZQV		ZQV 1.5/R 3.5/2 GE	1754210000	ZQV 1.5/R 3.5/2 GE	1754210000
		ZQV 1.5/R 3.5/3 GE	1754220000	ZQV 1.5/R 3.5/3 GE	1754220000
		ZQV 1.5/R 3.5/4 GE	1754230000	ZQV 1.5/R 3.5/4 GE	1754230000
		ZQV 1.5/R 3.5/5 GE	1754240000	ZQV 1.5/R 3.5/5 GE	1754240000
		ZQV 1.5/R 3.5/6 GE	1754250000	ZQV 1.5/R 3.5/6 GE	1754250000
		ZQV 1.5/R 3.5/7 GE	1754260000	ZQV 1.5/R 3.5/7 GE	1754260000
		ZQV 1.5/R 3.5/8 GE	1754270000	ZQV 1.5/R 3.5/8 GE	1754270000
		ZQV 1.5/R 3.5/9 GE	1754280000	ZQV 1.5/R 3.5/9 GE	1754280000
		ZQV 1.5/R 3.5/10 GE	1754290000	ZQV 1.5/R 3.5/10 GE	1754290000
		ZQV 1.5/R 3.5/30 GE	1754300000	ZQV 1.5/R 3.5/30 GE	1754300000
Tools					
SDI		Screwdriver	SDI	9008370000	SDI
Marking Tags					
		Print			
DEK		Consecutive vertical	DEK 5/3.5*	1762320001	DEK 5/3.5*
		Special print	DEK 5/3.5	1767730000	DEK 5/3.5
		Blank	DEK 5/3.5	1755270000	1755270000
100 tags per card					

*Part numbers shown are for a single card of pre-printed tags numbered 1-10. Change last four digits to order desired sequence. For example, 0001 (1-10), 0011 (11-20), etc.